

## **METHOD OF MONITORING ESC LEVELS AND PROTECTIVE DEVICES UTILIZING THE METHOD**

### **FIELD OF THE INVENTION**

The present invention relates generally to ESC monitoring devices and ESC  
5 protective devices, and more particularly is a method of monitoring triboelectric current  
generated in an operator's body, and thereby controlling ESC levels on the operator's  
body.

### **BACKGROUND OF THE INVENTION**

The present invention is based on the underlying mechanisms which cause  
electrostatic potentials to build up on human or other bodies. These mechanisms are  
used to provide improved and simplified methods for elimination of electrostatic  
potentials. The present invention also addresses the voltage potentials which are  
capacitively coupled into human or other bodies by power distribution wiring or by other  
naturally occurring or man-made electric fields.

15 The build up of electrostatic potentials on the human body when a person walks  
over a carpeted surface and when that person subsequently feels the unpleasant  
discharge when touching a door-knob has been experienced by countless numbers of  
people. Likewise, existence of capacitively coupled low frequency potentials, mostly

from power distribution wiring, can be relatively easily demonstrated by touching an input of an audio amplifier with a finger, which results in a loud hum emanating from the speakers.

The capacitively coupled voltage potentials from power distribution wiring have been traditionally largely ignored because their peak amplitudes are relatively small in comparison with the ones from electrostatic origin. In practice, when measuring these potentials, one finds peak amplitudes well below one kilovolt, whereas peak amplitudes from triboelectric charging are easily an order of magnitude higher. The neglect is further compounded by the fact that a human body discharge below 3 kilovolts is usually not physically felt. However, state of the art electronic devices and micro-structures have become so electrostatic discharge sensitive that one can no longer neglect the effects of low voltage potential discharges such as the ones from capacitively coupled low power line electric fields. All further references to human body voltage potentials in the application therefore imply potentials of triboelectric origin as well as potentials resulting from capacitively coupled electric fields.

In order to reduce and eliminate the detrimental effects of voltage potential discharges from human bodies, a number of devices have been developed. The most common of these devices is the "grounded wrist strap". The grounded wrist strap is basically a wrist-worn bracelet made of a conductive material. The bracelet makes electrical contact with a person's skin, and is connected to protective earth or other electrical common reference plane (subsequently referred to as the "ground") via a lead wire. Usually a resistor with a value of at least one megaohm is inserted in this

path-to-ground. The choice of the resistance value is a compromise between the need to adequately bleed-off the voltage potential charges, and, the need to avoid electric shock and / or electrocution when a person wearing such a grounded bracelet accidentally touches a live power distribution wire.

5           However, as shall be demonstrated below, the 1 Mohm or higher resistor does not reduce the voltage potentials sufficiently close to zero, and does thus not provide adequate protection during handling of state of the art electronic structures and devices. Under certain circumstances, instantaneous peak voltages of tens to hundreds of volts can be measured in spite of such grounding. State of the art Magneto Resistive (GMR, TMR, etc...) magnetic disk drive heads and sub-micron semiconductor structures can be destroyed with a human body voltage discharge of as low as 5 volts.

10  
15  
20           In addition to the wrist straps, it is also common industry practice to use "Workstation Monitors" in conjunction with the wrist straps. The purpose of the workstation monitors is at least twofold: (1) to establish a controlled path-to-ground, and, (2) to verify whether or not a wrist strap is being properly worn. Verification of whether or not a wrist strap is being properly worn is usually accomplished by dividing the wrist strap into two sections isolated from each other. In a typical detection approach, a small measuring current is sent through the wearer's skin between the isolated sections. By measuring the voltage drop across the isolated sections, a decision can be made whether the user's wrist is present or not. If a wrist is indeed present, it is further assumed that a proper connection to ground most likely exists.

The disadvantages of existing wrist straps, whether the split or the non-split

version, in conjunction with their existing workstation monitors, are as follows:

1. The 1 Mohm or higher resistor in the path-to-ground allows for body voltage potential excursions well beyond the safe limits of state of the art electronic structures and devices.

5           2. The value of the resistor in the path-to-ground cannot be lowered due to safety considerations.

3. None of the existing wrist strap / workstation monitor combinations determine with scientific certainty whether a true path from wrist to ground actually exists. All known approaches rely on the assumption that the hardware components used in this path seldom fail, and, therefore, the path is assumed to be of high integrity.

10           4. The interface between commonly used wrist strap materials and the human skin is not optimum. Well understood bioelectric effects cause variability in the contact resistance. Bioelectric potentials, because of the ionic nature of the skin / wrist strap interface, do interfere with the small measurement currents used in the split wrist strap approaches. As will be demonstrated later, it is unlikely that existing wrist straps will  
15           ever allow reliable and repeatable paths-to-ground of sufficiently low resistance, so as to meet the necessary 5 volt and lower sensitivities.

20           5. Certain split wrist strap measurement circuits in existing workstation monitors apply voltages above 5 volts to the wrist-under-test, thus charging the body capacitance to these levels, hence possibly contributing to device destruction rather than to their protection.

The present invention intends to improve on or eliminate all these constraints and

limitations. The present invention establishes a method of monitoring and controlling electrostatic charge on a human body. The method utilizes the discovery that the first order phenomenon in the charging of a human body to a voltage potential is in fact an electrical current, and that this current is driven from a near perfect current source of atomic nature. Proof of existence of this triboelectric current can be easily reproduced and demonstrated by connecting a human-under-test to a Current Amplifier, such as the Keithly 428 or equivalent, or, to a simple homemade current-to-voltage operational amplifier circuit with a 1 microamp per volt conversion gain. The output of the amplifier can be observed with a suitable recorder or oscilloscope while the human-under-test walks over a typical electrifying floor surface. In order to eliminate interference from often overwhelming capacitively coupled stray electric fields, the test is best done in a shielded room. Peak triboelectric currents generated by typical shoe sole / floor surface interactions were found to be as high as tens of microamperes. However, the vast majority, estimated at better than 95%, do not exceed 10 microamperes.

The voltage potential which develops on a human body, and which is measurable with any suitable electrometer or electrostatic voltmeter, is thus a direct result of a triboelectric current charging the body capacitance to an instantaneous voltage according to the general equation  $dv=(i*dt)/C$ . The typical body capacitance is 100 to 150 picofarads, and depends on the size, shape and posture of the body. In fact, the body voltage potential will continuously vary because of the continuous body shape or posture variations, all of which will change the body capacitance. This variation of body voltage potential is a secondary order effect in accordance with the law of conservation of

charge ( $C1 \cdot V1 = C2 \cdot V2 = Q$ ) which only can take place after the body capacitance was initially charged with a triboelectric current.

For purposes of electrical circuit analysis, the charging phenomenon can be modelled with an equivalent circuit comprising the triboelectric current source  $i(t)$ , the body capacitance  $C$ , and the resistive path-to-ground  $R$  is shown in Fig. 1.  $R$  represents the parallel circuit of all intentional (such as the 1 Mohm or higher bleeder resistor) and unintentional (such as conductive and ionic leakage paths) resistive paths between the body and ground. From a circuit analysis or spice simulation perspective, it is a first-order circuit driven by a non-constant current source. The source is non-constant because the interactions between the shoe sole and the floor surface are erratic and unpredictable. The total response of this circuit, which yields the instantaneous body voltage potential  $v(t)$ , invariably starts off with a part which is "transient" in nature (a person starting to walk, for example, or having occasional and infrequent shoe-to-surface interactions for example) and may even out to a "steady state" type response when, for example, a person walks at a steady and regular pace for some distance. Mathematical circuit analysis and/or Spice simulation will show that the peak amplitude of  $v(t)$  under the "transient" regime can be significantly higher than the one found under the "steady state" regime. This can be easily verified experimentally by measuring the body voltage potentials with a suitable electrometer or electrostatic voltmeter. The peak voltages measured during a person's initial steps will be considerably higher than the ones measured during the balance of the walk. By the same token, and operator sitting at a workstation, and shuffling his / her feet occasionally and infrequently will produce

considerably higher body voltage excursions that the same operator shuffling his / her feet continuously.

A typical current waveform associated with a single step with a nonconductive shoe on a non-conductive carpeted surface is shown in Fig. 2. The waveform can be broken down into four distinct segments: A) heel up, B) ball of the foot up, C) heel down, and, D) ball of the foot down. While the wave shape will generally approximate that shown in Fig. 2, the polarity of the waveform will depend on the specific materials present in a given shoe-to-surface interaction. The same shoe tracked in Fig. 2 would produce a waveform with reversed polarity if the floor surface is different, for instance a hardwood laminate.

When a person is grounded through a resistor, as in existing wrist strap protective devices, triboelectric current  $i(t)$  is forced through the parallel circuit formed by the grounding resistor  $R$  and body capacitance  $C$ . The waveform and the peak amplitude of the resulting voltage ( $v(t)$ ) across the parallel circuit can be determined via mathematical and/or experimental methods. The peak amplitude will be proportional to both the peak amplitude of  $i(t)$  and the speed with which  $i(t)$  varies over time ( $di/dt$ ). Experimentally, it has been determined that peak current amplitudes of tens of microamps and rates of rise as high as 5 milliamps/sec are not uncommon. When a current transient of this nature is forced to flow through a parallel combination comprising a 1 Mohm grounding resistor and a 100 picofarad body capacitance, a peak voltage potential  $v(t)$  of tens of volts will result. Similarly, if the resistance in the path-to-ground is 10 Mohm, as in certain existing wrist strap and workstation monitor combinations, a

peak body voltage potential of over one hundred volts will result. In both cases, these amplitudes are clearly beyond the survival limits of state of the art electronic structures and devices.

As mentioned above, it was determined experimentally that the majority of shoe-to-floor-surface interactions produce triboelectric peak currents not exceeding 10 microamperes, with rise times not exceeding 2.5 milliamps/second. From this basis, one can determine via mathematical and/or experimental methods, that for a given body capacitance of 100 picofarads, one can limit the peak body voltage excursions to 1 volt if the resistor value in the path-to-ground does not exceed 100 kilohm. For all practical purposes, with path-to-ground resistances below a few hundred kilohm, one can approximate the peak body voltage excursion by simple multiplication of the peak current times the path-to-ground resistance. The error made by omitting the effect of the body capacitance is minimal. The 100 kilohm resistor value of course includes the contact resistance between the wrist strap and the skin of its wearer. As mentioned above, the resistance of current art wrist straps is highly erratic and unpredictable. In fact, values of hundreds of kilohms on persons with dry skin, particularly when compounded by motion artifact, are quite common. It is thus highly unlikely that the existing wrist straps in combination with their existing workstation monitors will allow for the safe handling of very sensitive state-of-the-art electronic devices and structures which have damage thresholds of 5 volts or less.

Accordingly, it is an object of the present invention to provide a protection / monitoring system that limits potential body voltage excursions within the safe limits of



state of the art electronic structures and devices.

It is a further object of the present invention to provide a methodology that allows the resistance in the path-to-ground to be safely lowered.

It is a still further object of the present invention to provide a means to determine with scientific certainty whether a true path from wrist to ground actually exists.

It is another object of the present invention to provide an improved interface between wrist strap materials and the human skin.

It is still another object of the present invention to reduce or eliminate voltages applied to the wrist-under-test, thereby reducing the body voltage potential.

## SUMMARY OF THE INVENTION

The present invention is a method of monitoring ESC on a human body comprising the following steps:

a) Connecting the human body to a "Quasi Virtual Ground". The maximum resistance in the path-to-ground does not exceed 10 Kohm, thus insuring that the majority of peak body voltage potential excursions will not exceed 100 millivolts. For all practical purposes, it comes down to the triboelectric current being shunted directly to ground.

b) Providing contact with the human skin via one or more electrodes. The preferred type of electrode is a silver / silver chloride electrode. The chemical, mechanical and electrical properties of silver / silver-chloride electrodes in contact with human skin have been studied extensively by the medical industry and are thus well

optimized and understood. With the addition of an adequate gel between the electrodes and the skin, the contact resistance is typically below 2 Kohm, and, the resistance is stable over reasonable amounts of time (days), and is virtually not prone to motion artifact. The silver / silver chloride electrodes could be part of a designed for the purpose bracelet, or they could be pre-gelled disposable adhesive patches similar to the ones used for medical electrocardiography (Holter electrodes). Whatever the means of making contact with the skin, it is very important for the contact resistance to be as low as practical. As a fall back method, one can also use industry standard wrist straps, either the split or the non-split versions, with the herein described workstation monitor, but because of their inherent high and unstable skin contact resistance, body voltage potential excursions exceeding the 5 volt threshold limit are to be expected. Application of a topical conduction improving gel on the wrist could alleviate some of the problems. For the sake of simplification, the means of contact with the skin will be further referred to as the "body electrode".

c) Continuously monitoring the triboelectric current  $i(t)$  flowing into the "Quasi Virtual Ground" terminal. The amplitude and polarity of the triboelectric current can be made visible on any suitable visual display device such as, for example, a recorder, an oscilloscope, or a bar graph display with a linear, logarithmic, or custom scale.

d) Determining whether or not a person is properly wearing his / her body electrode and whether or not a true path from wrist to ground actually exists. This determination can be accomplished through a number of methods, none of them requiring a measuring current to be sent through a split body electrode. The methods

will be described in detail below.

e) Including circuitry that immediately interrupts the path-to-ground when a dangerously large current is detected. In the present arrangement, with the path-to-ground being of relatively low resistive value, a danger for electroshock and/or electrocution exists in case of accidental contact with a live power distribution wire. Circuitry is therefore included in this novel workstation monitor which will detect and interrupt the path-to-ground nearly instantaneously. A suitable type of visual and audible alarm will be activated concurrently. Deliberate manual reset will be required in order to reestablish the path-to-ground.

f) Including circuitry that immediately interrupts the path-to-ground when the power supply to the workstation monitor is interrupted, either intentionally or accidentally. The path-to-ground will remain open until the deliberate manual reset has been executed.

An advantage of the present invention is that it limits potential body voltage excursions within the safe limits of state of the art electronic structures and devices.

Another advantage of the present invention is that it provides a means to determine with scientific certainty whether a true path from wrist to ground actually exists.

These and other objects and advantages of the present invention will become apparent to those skilled in the art in view of the description of the best presently known mode of carrying out the invention as described herein and as illustrated in the drawings.

## BRIEF DESCRIPTION OF THE DRAWINGS

Fig. 1 is a circuit diagram showing the triboelectric current source  $i(t)$ , the body capacitance  $C$ , and the resistive path-to-ground  $R$ .

Fig. 2 shows a typical triboelectric current waveform associated with a single step of a person wearing a nonconductive shoe on a non-conductive carpeted surface.

5 Fig. 3 shows a block diagram of one embodiment of the workstation monitor according to the present invention.

Fig. 4 is a block diagram of a workstation monitor with certain stages executed with a microprocessor.

10 Fig. 5 depicts a block diagram of an implementation of the workstation monitor utilizing minimal component count.

Fig. 6 shows a diagram of a further simplified workstation monitor.

Fig. 7 depicts possible arrangements of bracelet type body electrodes with a switch incorporated in the bracelet.

Fig. 7a is a non-split bracelet with a "normally open" switch.

Fig. 7b depicts a non-split bracelet with a "normally closed" switch.

Fig. 7c is a split bracelet with a "normally open" switch.

Fig. 7b depicts a split bracelet with a "normally closed" switch.

Fig. 8 shows a workstation monitor detection scheme utilizing a shared conductor.

Fig. 9 is a block diagram for a redundant path-to-ground arrangement.

20 Fig. 10 shows an ESC Workstation arrangement based on two body electrodes.

## DETAILED DESCRIPTION OF THE INVENTION

The present invention is a method of controlling and monitoring the voltage potential on a human body comprising the following steps:

a) Connecting the human body to a "Quasi Virtual Ground". The maximum resistance in the path-to-ground does not exceed 10 Kohm, thus insuring that the majority of peak body voltage potential excursions will not exceed 100 millivolts. For all practical purposes, it comes down to the triboelectric or other currents being shunted directly to ground.

b) Providing contact with the human skin via one or more electrodes, preferably silver / silver chloride electrodes. The chemical, mechanical and electrical properties of silver / silver-chloride electrodes in contact with human skin have been studied extensively by the medical industry and are thus well optimized and understood. With the addition of an adequate gel between the electrodes and the skin, the contact resistance is typically below 2 Kohm, and, the resistance is stable over reasonable amounts of time (days), and is not prone to motion artifact. The silver / silver chloride electrodes could be part of a designed for the purpose bracelet, or they could be pre-gelled disposable adhesive patches similar to the ones used for medical electrocardiography (Holter electrodes). Whatever the means of making contact with the skin, it is very important for the contact resistance to be as low as practical. As a fall back method, one can also use industry standard wrist straps, either the split or the non-split versions, with the here described workstation monitor, but, because of their inherent high and unstable contact resistance, body voltage potential excursions exceeding safe levels are to be expected. Application of a topical conduction improving

gel on the wrist could alleviate some of the problems. For the sake of simplification, the means of contact with the skin will be further referred to as the "body electrode".

c) Continuously monitoring the triboelectric current  $i(t)$  flowing into the "Quasi Virtual Ground" terminal. The amplitude and polarity of the triboelectric current can be made visible on any suitable visual display device such as, for example, a recorder, an oscilloscope, a bar graph display with a linear, logarithmic, or custom scale, or any other suitable display.

d) Determining whether or not a person is properly wearing his / her body electrode. This determination can be accomplished through a number of methods, none of them requiring a measuring current to be sent through a split body electrode. The methods will be described in detail below.

e) Including circuitry that immediately interrupts the path-to-ground when a dangerously large current is detected. In the present arrangement, with the path-to-ground being of relatively low resistive value, a danger for electroshock and/or electrocution exists in case of accidental contact with a live power distribution wire. Circuitry is therefore included in this novel workstation monitor which will detect and interrupt the path-to-ground instantaneously. A suitable type of visual and audible alarm will be activated concurrently. Deliberate manual reset will be required in order to reestablish the path-to-ground.

f) Including circuitry that immediately interrupts the path-to-ground when the power supply to the workstation monitor is interrupted, either intentionally or accidentally. The path-to-ground will remain open until the deliberate manual reset has been executed.

#### **D tection Means:**

In the present invention, a number of techniques may be used to provide a means for detection of whether a person is properly grounded or not. These techniques are not mutually exclusive. They can be used in various combinations so as to enhance the overall reliability of the detection method.

Detection of whether or not a bracelet type body electrode is correctly present on a wrist can be made by including an electromechanical switch in the bracelet itself. If sufficient pressure is present on the lever mechanism actuating the switch, contact closure, or opening, will result. A lead wire containing at least two conductors, a first lead wire to establish the path-to-ground, and a second lead wire for detection of the switch closure (or opening) is used between the bracelet and the workstation monitor. The circuitry for this arrangement is described in detail in the Circuit Description section following below.

Another method of detection in the present invention is based on observing the presence or absence of bursts of triboelectric current flow over a certain period of time. In most practical situations, there will be continuous bursts because of an operator's minute involuntary shoe sole / floor surface interactions. If no current flow is detected for a certain period of time, ten seconds for example, an attention drawing visual / audible alarm will be activated. A lack of current flow implies that either the operator is no longer properly connected to the workstation monitor, or that he or she happened to be sufficiently motionless so as to not produce triboelectric current bursts of a certain minimal amplitude during this time period. In the latter case, a minor shuffling of the

shoes will produce sufficient current to deactivate the alarm. A lead with a single conductor connects the electrode to the workstation monitor. The alarm can be deactivated by unplugging this lead. A suitable detection mechanism, such as a keyed-for-the-purpose lead connector at the workstation monitor, would serve this purpose.

5 Details of controlling circuitry layouts for this means of detection are given in the Circuit Description section following below.

Still another method of detection is based on the use of split body electrodes such as two disposable patches, electrically isolated from each other, or a split version bracelet. Both body electrodes are connected individually, and are part of two identical virtual ground paths inside the workstation monitor. When worn properly, both paths-to-ground will have similar resistances, and half of the triboelectric current will thus flow down each path. If this is not the case, for example, if one of the paths is open or the contact with the skin has deteriorated, then the current distribution will no longer be equal. Controlling circuitry, described below in the Circuit Description section, can easily detect this situation, and activate an appropriate alarm to draw the operator's attention.

Yet another method of detection is also based on the use of split body electrodes. In this case, one of the electrodes serves to establish the path-to-ground for the triboelectric current, whereas the second electrode is used to measure the body voltage potential. If, for whatever reason, the path-to-ground resistance in the first electrode circuit increases beyond a set limit, the body voltage potential excursion will become unacceptably high. The electrode of the second circuit, connected to a voltmeter type circuit with adequately high input impedance, will detect these voltage excursions, and



activate an alarm.

### **Circuit Description:**

Fig. 3 shows a block diagram of one implementation of the novel workstation monitor of the present invention. A single wire lead connects a body electrode 100 such as a single disposable patch electrode or a non-split wrist strap to the workstation monitor. If a patch electrode is used, its location on the body is not critical, and can be selected so as to minimize the interference of the lead wire with the operator's activity. This freedom in attachment of patch electrodes is a distinct advantage over wrist strap type devices which, by design, can only be worn on a wrist. Experience has shown that the level of interference with tools and equipment on a work surface created by a lead connected at the shoulder of an operator, for example, is far less intrusive than a lead attached at the wrist. Excluding the resistance of the copper wire itself, there are no added resistors in the lead connecting the skin contact electrode to the workstation monitor. A suitable keyed connector 12 at the workstation monitor allows for detection of whether or not the lead is plugged in. The key can be electrical, mechanical, or a combination of the two. Fig. 3 depicts an electrical key with a resistor of a certain value. Different values of the resistor can be assigned to identify different models of body electrodes. If the keyed connector 12 is not plugged in, the alarm will be disabled. Detection of a properly worn body electrode is accomplished by the earlier mentioned method of observing the existence of occasional bursts of triboelectric current which are typically associated with shoe sole / floor surface interactions of an operator.

The process begins with the triboelectric current entering the ground fault sensing / relay / current limit stage 1. That signal is then processed through a current-to-voltage converter 2, through a 50/60 Hz notch filter 3, and then through an absolute value amplifier 4. The purpose of the absolute value amplifier 4 is to convert bipolar signals at its input into positive unipolar signals at its output. The unipolar output drives a display 5. In the preferred embodiment, the display 5 is a logarithmic bar graph with a 40 dB span. The bar graph of the preferred embodiment comprises 11 LED's spaced 4 dB's apart. The least significant LED will correspond to  $0.1 \mu\text{A}$  of triboelectric current, and the most significant LED will correspond to  $10 \mu\text{A}$ . Many other executions of the display 5 are suitable for use in the present invention, and are known to those skilled in the art.

From the LED bar graph display 5, a signal J is picked off to drive activity detector stage 8. The activity of the least significant LED is monitored by activity detector 8. If this LED stayed off for more than ten seconds, meaning there was no triboelectric current activity for ten seconds, the activity detector 8 would time out, and send a command to 50 mS / 5S astable multivibrator stage 9. Activity detector stage 8 comprises a retriggerable monostable multivibrator. Concurrently with this processing, a signal B is picked off at the ground fault sensing stage 1, and goes to the window detector 6, and from there to the ground fault bistable multivibrator 7 (Ha and Hb). If a positive or negative current would flow in the path-to-ground, exceeding the threshold limits set in window detector stage 6, signals Ha and Hb will activate the ground fault bistable multivibrator stage 7 immediately, which in turn, will cause relay contact in the ground

fault sensing / relay / current limit stage 1 to open instantly, thus interrupting the path-to-ground. Both the activity detector stage 8, which detects the presence of triboelectric current bursts, and the ground fault bistable multivibrator 7 have output signals M and 0 which drive 50 mS / 5 S astable multivibrator 9 and 0.5 S / 0.5 sec astable multivibrator 11 respectively. Multivibrators 9 and 11 drive a visual / audible alarm 10. In this particular embodiment, a visual / audible 50 mS beep will repeat every five seconds to indicate a lack of triboelectric current bursts, and will beep continuously, (0.5 sec on, 0.5 sec off), if an accidental contact with a live power distribution wire occurs.

Ground fault bistable multivibrator 7 output signal C will cause a relay to open in stage 1 if an operator were to accidentally touch a live power wire. Ground fault bistable multivibrator stage 7 output signal G ensures blanking of all the LED's of the bar graph in display stage 5 as long as stage 7 has not been reset manually by signal L (GFI reset). Signal K (power-on fail safe) insures that the bistable multivibrator in stage 7 is set to the proper logical state when an intentional or unintentional power interruption has occurred. At power-up, the relay in stage 1 will always come up in the open (fail safe) state. Assertion of the reset GFI input L is required in order to resume service. Not shown in Fig. 3 are the power supply circuits for the various stages and circuits. It will be obvious to those skilled in the art that this workstation monitor will incorporate power supply circuits. Power is derived from the facilities' regular AC power distribution. It is down-converted and rectified to voltage levels compatible with standard electronic circuits. The power line cord of the workstation monitor includes the standard three wires, one of them being the ground wire (the "green wire"). The path-to-ground for the

triboelectric current includes this green wire. The current cannot flow, that is, there is no current, if the green wire is not present, or if for some reason, the green wire is not connected to earth, either by accident or by an intentional act. This will result in an alarm situation, identical to the one described earlier under the lack of triboelectric bursts. Fig. 4 shows a block diagram of a workstation monitor with equivalent functionality to that shown in Fig. 3, but in which certain of the stages are executed with a microprocessor. In the scheme illustrated in Fig. 4, a data I/O bus allows for communications between the workstation monitor and a possible remote data acquisition system.

Fig. 5 shows a block diagram of a "bare bones" implementation of a workstation monitor. Portions of this circuit are identical to the previous one, however, all stages not essential in establishing the path-to-ground and the ground fault sensing have been omitted. The triboelectric current enters the circuit at stage 1 (ground fault sensing / relay / current limiter) and is conducted into the ground (A).

Signal B is picked off at stage 1, and enters window detector 6. If the amplitude of signal B exceeds certain levels (such as in the case of an accidental touching of a live power wire), signals Da and Db will set the GFI bistable multivibrator stage 7 in a state such as to insure that the relay contact in stage 1 opens the path-to-ground (signal C). Input signal E (Power-on Fail Safe) to the GFI bistable multivibrator stage 7 insures that the relay is always in the open state when power is applied to the workstation monitor. The relay can be closed by manually resetting stage 7 with the reset GFI signal F. Output G from the GFI bistable multivibrator stage 7 will cause the audible/visual alarm

means 10 to be activated.

An even further simplification of a "minimal" workstation monitor is illustrated in Fig. 6. This circuit is based on commercially available Ground Fault Interrupter Integrated Circuits such as the National Semiconductor LM1851. The triboelectric current is picked up by body electrode 100 and flows through a path comprising the primary of current transformer 14, relay contacts 16, and bleeder resistor 18. The value of this resistor added to the value of the skin-to-electrode resistance will largely determine the worst case body voltage potential excursion. (This assumes that all other resistors in the path are negligible with respect to the bleeder resistor 18 and the skin electrode.) The secondary of the current transformer 14 is connected to the input of ground fault interrupter integrated circuit 20. If an operator accidentally touches a 50 or 60 Hz live power distribution wire, a potentially dangerous current will flow through the path-to-ground. When the current exceeds a certain level, such as for example specified in Underwriter's Laboratories' publication UL 943, circuit 20 will cause relay contact 16 to open, thus interrupting the path-to-ground. The circuitry in IC 20 is executed such that contact 16 can only close when circuit 20 is properly powered, either from an AC power line derived power source, or from batteries.

The bistability of the relay action can be executed either electronically in IC 20 in conjunction with reset contact 22, or electromechanically in relay 17 with a suitable mechanical reset mechanism, or with a combination of the two. A further improvement to the monitor circuit is the addition of test winding 26 to the current transformer. Closure of contact 28 allows a test current to flow with amplitude such that a fault current

is simulated. The test current is derived from the power source.

#### **Additional Detection Means:**

Figs. 7-10 show additional arrangements and circuits which allow positive determination of whether a wrist strap is properly worn or not. Figs. 7a-d depict possible arrangements of bracelet type body electrodes with a switch incorporated in the bracelet. Fig. 7a is a non-split bracelet 100 with a "normally open" switch 101. When the bracelet is not properly worn or insufficiently tight around the wrist, the contact will be open. Fig. 7b depicts a non-split bracelet 100 with a "normally closed" switch 101'. Similarly, Figs. 7c and 7d respectively depict split bracelets 100' with a "normally open" switch 101 and a "normally closed" switch 101'.

Connectors 102 allow connection with the circuitry of the workstation monitor. The connectors 102 may or may not include electrical keying, mechanical keying, or a combination of both. Keying 103 is accomplished by assigning a certain value resistor for a given type of wrist strap. This allows the workstation monitor to recognize which body electrode is being used.

Certain detection schemes will allow sharing of a conductor, thus reducing the number of conductors required in the lead between the body electrode and the workstation monitor. In the circuit shown in Fig. 8, for example, the conductor connected to one of the switch poles is common with the path-to-ground conductor. Shown is a non-split body electrode 100 with a normally closed switch 101'. One of the poles of the switch 101' is electrically connected with the body electrode 100. A dual conductor lead with a suitable connector 104 at the other side of switch 101' allows for connection to

the workstation monitor circuitry, which is substantially identical to the circuit illustrated in detail in Fig. 3.

Two stages have been added for the detection scheme shown in Fig. 8 that allow the monitor to determine if a user is wearing the body electrode 100 properly, the stages being an oscillator circuit 30 and a bandpass filter / detector 32. An output signal from oscillator circuit 30, when normally closed switch 101 is in the closed position (the wrist strap is not worn properly), is provided as an input to the band pass filter / detector 32. This signal thus travels down the same path-to-ground conductor as the triboelectric current. After processing, an output signal A is generated by the band pass filter / detector 32 which signals the workstation monitor circuitry that switch 101' is closed, and activates an alarm in the workstation monitor circuit. This situation occurs only when the body electrode 100 is not being worn properly. When the body electrode 100 is properly worn, switch 101' will be open, and intended operation of the workstation monitor continues.

Fig. 9 shows the block diagram of a detection method based on a dual body electrode, for a redundant path-to-ground arrangement. Two body electrodes 100, which should be isolated from each other, are connected to identical signal shaping circuit stages which are substantially identical to those described in relation to Fig. 3, and which comprise a ground fault sensing / relay / current limit stage 1, a current-to-voltage converter 2, and a 50/60 Hz notch filter 3. Since the circuits in the two signal shaping paths are identical, and provided the contact resistances between the skin and the electrodes 100 are substantially the same, equal currents will flow through both

paths-to-ground. Signals I and L will therefore be substantially identical. Signals I and L are further processed in parallel through a sum amplifier 18 and a difference amplifier 20. Output signal M, having passed through the sum amplifier 18, is therefore proportional to the sum of the fractional triboelectric currents flowing down the two paths-to-ground, and thus represents the total triboelectric current generated by the shoe sole / surface interaction. Signal M is then processed through an absolute value detector 4 and a display 5, similar to the process described relative to Fig. 3. Signal O at the output of difference amplifier 20 is proportional to the difference of the fractional triboelectric currents. As long as both paths-to-ground are substantially identical, signal O will be near zero. If, for whatever reason, one of the paths would be compromised, the amplitude of signal O will be different from zero. If the amplitude of signal O exceeds a set threshold level of window detector 6, the asymmetrical 50 mS / 5 S astable multivibrator 9 is triggered, thereby activating the visual / audible alarm 10, and thus announcing that one of the two paths-to-ground has been compromised, and that one of the body electrodes is no longer in proper contact with the operator's skin.

The detection of an accidental touch with a live power distribution wire is made redundant by using two window detector stages 6, each of them capable of triggering GFI bistable multivibrator 7. Both paths-to-ground have isolated-from-each-other relay contacts in their circuits. The relay contacts are located in the GFI sensing / relay / current limit stages, and interrupt the path to ground.

Fig. 10 the block diagram of another workstation arrangement based on two body electrodes 100. In this arrangement, only a first body electrode 100 establishes the



path-to-ground, whereas a second body electrode 100 is used to measure body voltage potential. The path-to-ground circuitry is substantially identical to those described above with reference to Fig. 3. The body voltage potential path includes an input protection circuit 38, followed by a voltage follower 40, which represents a very high input impedance to the body electrode 100. These stages are followed by a 50/60 Hz notch filter 3.

Signal N, proportional to the body voltage potential, goes to a window detector 6, and, if the amplitude of signal N exceeds certain preset values, signal Oa or Ob will trigger the astable multivibrator 9, which in turn, will set off the visual / audible alarm 10.

The amplitude of signal N can only exceed the threshold levels of window detector 6 only when the triboelectric current path-to-ground is compromised.

Switch 44 allows either the triboelectric current or the body voltage potential to be displayed on a suitable display 42. An absolute value detector 4 may be included in the display circuitry if desired. It is also possible to eliminate selector switch 44 by adding a second display 42 so that both channels can be displayed simultaneously. The triboelectric current is then displayed on a first display 42, and the body voltage potential is shown on a second display 42. The absolute value detector 4 and display 42 are substantially identical to those described with reference to Fig. 3.

Because of the very high input impedance of the voltage channel, degradation of the skin-to-electrode resistance in the voltage channel does not come into play in the accuracy of the voltage measurement. The body voltage measurement is not compromised because the input impedance of the voltage amplifier chain is orders of

magnitude higher than the skin-to-electrode resistance. The approach shown in Fig. 10 is thus well suited for use with existing split wrist straps with their inherently unreliable skin-to-electrode resistance. For example if the effect of a conduction improving gel between wrist and electrode wears off, thereby compromising the integrity of the path-  
5 to-ground, an operator's attention will be drawn by increasingly frequent alarms.

The above disclosure is not intended as limiting. Those skilled in the art will readily observe that numerous modifications and alterations of the device may be made while retaining the teachings of the invention. Accordingly, the above disclosure should be construed as limited only by the restrictions of the appended claims.

10  
11  
12  
13  
14  
15  
16  
17  
18  
19  
20  
21  
22  
23  
24  
25  
26  
27  
28  
29  
30  
31  
32  
33  
34  
35  
36  
37  
38  
39  
40  
41  
42  
43  
44  
45  
46  
47  
48  
49  
50  
51  
52  
53  
54  
55  
56  
57  
58  
59  
60  
61  
62  
63  
64  
65  
66  
67  
68  
69  
70  
71  
72  
73  
74  
75  
76  
77  
78  
79  
80  
81  
82  
83  
84  
85  
86  
87  
88  
89  
90  
91  
92  
93  
94  
95  
96  
97  
98  
99  
100  
101  
102  
103  
104  
105  
106  
107  
108  
109  
110  
111  
112  
113  
114  
115  
116  
117  
118  
119  
120  
121  
122  
123  
124  
125  
126  
127  
128  
129  
130  
131  
132  
133  
134  
135  
136  
137  
138  
139  
140  
141  
142  
143  
144  
145  
146  
147  
148  
149  
150  
151  
152  
153  
154  
155  
156  
157  
158  
159  
160  
161  
162  
163  
164  
165  
166  
167  
168  
169  
170  
171  
172  
173  
174  
175  
176  
177  
178  
179  
180  
181  
182  
183  
184  
185  
186  
187  
188  
189  
190  
191  
192  
193  
194  
195  
196  
197  
198  
199  
200  
201  
202  
203  
204  
205  
206  
207  
208  
209  
210  
211  
212  
213  
214  
215  
216  
217  
218  
219  
220  
221  
222  
223  
224  
225  
226  
227  
228  
229  
230  
231  
232  
233  
234  
235  
236  
237  
238  
239  
240  
241  
242  
243  
244  
245  
246  
247  
248  
249  
250  
251  
252  
253  
254  
255  
256  
257  
258  
259  
260  
261  
262  
263  
264  
265  
266  
267  
268  
269  
270  
271  
272  
273  
274  
275  
276  
277  
278  
279  
280  
281  
282  
283  
284  
285  
286  
287  
288  
289  
290  
291  
292  
293  
294  
295  
296  
297  
298  
299  
300  
301  
302  
303  
304  
305  
306  
307  
308  
309  
310  
311  
312  
313  
314  
315  
316  
317  
318  
319  
320  
321  
322  
323  
324  
325  
326  
327  
328  
329  
330  
331  
332  
333  
334  
335  
336  
337  
338  
339  
340  
341  
342  
343  
344  
345  
346  
347  
348  
349  
350  
351  
352  
353  
354  
355  
356  
357  
358  
359  
360  
361  
362  
363  
364  
365  
366  
367  
368  
369  
370  
371  
372  
373  
374  
375  
376  
377  
378  
379  
380  
381  
382  
383  
384  
385  
386  
387  
388  
389  
390  
391  
392  
393  
394  
395  
396  
397  
398  
399  
400  
401  
402  
403  
404  
405  
406  
407  
408  
409  
410  
411  
412  
413  
414  
415  
416  
417  
418  
419  
420  
421  
422  
423  
424  
425  
426  
427  
428  
429  
430  
431  
432  
433  
434  
435  
436  
437  
438  
439  
440  
441  
442  
443  
444  
445  
446  
447  
448  
449  
450  
451  
452  
453  
454  
455  
456  
457  
458  
459  
460  
461  
462  
463  
464  
465  
466  
467  
468  
469  
470  
471  
472  
473  
474  
475  
476  
477  
478  
479  
480  
481  
482  
483  
484  
485  
486  
487  
488  
489  
490  
491  
492  
493  
494  
495  
496  
497  
498  
499  
500  
501  
502  
503  
504  
505  
506  
507  
508  
509  
510  
511  
512  
513  
514  
515  
516  
517  
518  
519  
520  
521  
522  
523  
524  
525  
526  
527  
528  
529  
530  
531  
532  
533  
534  
535  
536  
537  
538  
539  
540  
541  
542  
543  
544  
545  
546  
547  
548  
549  
550  
551  
552  
553  
554  
555  
556  
557  
558  
559  
560  
561  
562  
563  
564  
565  
566  
567  
568  
569  
570  
571  
572  
573  
574  
575  
576  
577  
578  
579  
580  
581  
582  
583  
584  
585  
586  
587  
588  
589  
590  
591  
592  
593  
594  
595  
596  
597  
598  
599  
600  
601  
602  
603  
604  
605  
606  
607  
608  
609  
610  
611  
612  
613  
614  
615  
616  
617  
618  
619  
620  
621  
622  
623  
624  
625  
626  
627  
628  
629  
630  
631  
632  
633  
634  
635  
636  
637  
638  
639  
640  
641  
642  
643  
644  
645  
646  
647  
648  
649  
650  
651  
652  
653  
654  
655  
656  
657  
658  
659  
660  
661  
662  
663  
664  
665  
666  
667  
668  
669  
670  
671  
672  
673  
674  
675  
676  
677  
678  
679  
680  
681  
682  
683  
684  
685  
686  
687  
688  
689  
690  
691  
692  
693  
694  
695  
696  
697  
698  
699  
700  
701  
702  
703  
704  
705  
706  
707  
708  
709  
710  
711  
712  
713  
714  
715  
716  
717  
718  
719  
720  
721  
722  
723  
724  
725  
726  
727  
728  
729  
730  
731  
732  
733  
734  
735  
736  
737  
738  
739  
740  
741  
742  
743  
744  
745  
746  
747  
748  
749  
750  
751  
752  
753  
754  
755  
756  
757  
758  
759  
760  
761  
762  
763  
764  
765  
766  
767  
768  
769  
770  
771  
772  
773  
774  
775  
776  
777  
778  
779  
780  
781  
782  
783  
784  
785  
786  
787  
788  
789  
790  
791  
792  
793  
794  
795  
796  
797  
798  
799  
800  
801  
802  
803  
804  
805  
806  
807  
808  
809  
810  
811  
812  
813  
814  
815  
816  
817  
818  
819  
820  
821  
822  
823  
824  
825  
826  
827  
828  
829  
830  
831  
832  
833  
834  
835  
836  
837  
838  
839  
840  
841  
842  
843  
844  
845  
846  
847  
848  
849  
850  
851  
852  
853  
854  
855  
856  
857  
858  
859  
860  
861  
862  
863  
864  
865  
866  
867  
868  
869  
870  
871  
872  
873  
874  
875  
876  
877  
878  
879  
880  
881  
882  
883  
884  
885  
886  
887  
888  
889  
890  
891  
892  
893  
894  
895  
896  
897  
898  
899  
900  
901  
902  
903  
904  
905  
906  
907  
908  
909  
910  
911  
912  
913  
914  
915  
916  
917  
918  
919  
920  
921  
922  
923  
924  
925  
926  
927  
928  
929  
930  
931  
932  
933  
934  
935  
936  
937  
938  
939  
940  
941  
942  
943  
944  
945  
946  
947  
948  
949  
950  
951  
952  
953  
954  
955  
956  
957  
958  
959  
960  
961  
962  
963  
964  
965  
966  
967  
968  
969  
970  
971  
972  
973  
974  
975  
976  
977  
978  
979  
980  
981  
982  
983  
984  
985  
986  
987  
988  
989  
990  
991  
992  
993  
994  
995  
996  
997  
998  
999  
1000  
1001  
1002  
1003  
1004  
1005  
1006  
1007  
1008  
1009  
1010  
1011  
1012  
1013  
1014  
1015  
1016  
1017  
1018  
1019  
1020  
1021  
1022  
1023  
1024  
1025  
1026  
1027  
1028  
1029  
1030  
1031  
1032  
1033  
1034  
1035  
1036  
1037  
1038  
1039  
1040  
1041  
1042  
1043  
1044  
1045  
1046  
1047  
1048  
1049  
1050  
1051  
1052  
1053  
1054  
1055  
1056  
1057  
1058  
1059  
1060  
1061  
1062  
1063  
1064  
1065  
1066  
1067  
1068  
1069  
1070  
1071  
1072  
1073  
1074  
1075  
1076  
1077  
1078  
1079  
1080  
1081  
1082  
1083  
1084  
1085  
1086  
1087  
1088  
1089  
1090  
1091  
1092  
1093  
1094  
1095  
1096  
1097  
1098  
1099  
1100  
1101  
1102  
1103  
1104  
1105  
1106  
1107  
1108  
1109  
1110  
1111  
1112  
1113  
1114  
1115  
1116  
1117  
1118  
1119  
1120  
1121  
1122  
1123  
1124  
1125  
1126  
1127  
1128  
1129  
1130  
1131  
1132  
1133  
1134  
1135  
1136  
1137  
1138  
1139  
1140  
1141  
1142  
1143  
1144  
1145  
1146  
1147  
1148  
1149  
1150  
1151  
1152  
1153  
1154  
1155  
1156  
1157  
1158  
1159  
1160  
1161  
1162  
1163  
1164  
1165  
1166  
1167  
1168  
1169  
1170  
1171  
1172  
1173  
1174  
1175  
1176  
1177  
1178  
1179  
1180  
1181  
1182  
1183  
1184  
1185  
1186  
1187  
1188  
1189  
1190  
1191  
1192  
1193  
1194  
1195  
1196  
1197  
1198  
1199  
1200  
1201  
1202  
1203  
1204  
1205  
1206  
1207  
1208  
1209  
1210  
1211  
1212  
1213  
1214  
1215  
1216  
1217  
1218  
1219  
1220  
1221  
1222  
1223  
1224  
1225  
1226  
1227  
1228  
1229  
1230  
1231  
1232  
1233  
1234  
1235  
1236  
1237  
1238  
1239  
1240  
1241  
1242  
1243  
1244  
1245  
1246  
1247  
1248  
1249  
1250  
1251  
1252  
1253  
1254  
1255  
1256  
1257  
1258  
1259  
1260  
1261  
1262  
1263  
1264  
1265  
1266  
1267  
1268  
1269  
1270  
1271  
1272  
1273  
1274  
1275  
1276  
1277  
1278  
1279  
1280  
1281  
1282  
1283  
1284  
1285  
1286  
1287  
1288  
1289  
1290  
1291  
1292  
1293  
1294  
1295  
1296  
1297  
1298  
1299  
1300  
1301  
1302  
1303  
1304  
1305  
1306  
1307  
1308  
1309  
1310  
1311  
1312  
1313  
1314  
1315  
1316  
1317  
1318  
1319  
1320  
1321  
1322  
1323  
1324  
1325  
1326  
1327  
1328  
1329  
1330  
1331  
1332  
1333  
1334  
1335  
1336  
1337  
1338  
1339  
1340  
1341  
1342  
1343  
1344  
1345  
1346  
1347  
1348  
1349  
1350  
1351  
1352  
1353  
1354  
1355  
1356  
1357  
1358  
1359  
1360  
1361  
1362  
1363  
1364  
1365  
1366  
1367  
1368  
1369  
1370  
1371  
1372  
1373  
1374  
1375  
1376  
1377  
1378  
1379  
1380  
1381  
1382  
1383  
1384  
1385  
1386  
1387  
1388  
1389  
1390  
1391  
1392  
1393  
1394  
1395  
1396  
1397  
1398  
1399  
1400  
1401  
1402  
1403  
1404  
1405  
1406  
1407  
1408  
1409  
1410  
1411  
1412  
1413  
1414  
1415  
1416  
1417  
1418  
1419  
1420  
1421  
1422  
1423  
1424  
1425  
1426  
1427  
1428  
1429  
1430  
1431  
1432  
1433  
1434  
1435  
1436  
1437  
1438  
1439  
1440  
1441  
1442  
1443  
1444  
1445  
1446  
1447  
1448  
1449  
1450  
1451  
1452  
1453  
1454  
1455  
1456  
1457  
1458  
1459  
1460  
1461  
1462  
1463  
1464  
1465  
1466  
1467  
1468  
1469  
1470  
1471  
1472  
1473  
1474  
1475  
1476  
1477  
1478  
1479  
1480  
1481  
1482  
1483  
1484  
1485  
1486  
1487  
1488  
1489  
1490  
1491  
1492  
1493  
1494  
1495  
1496  
1497  
1498  
1499  
1500  
1501  
1502  
1503  
1504  
1505  
1506  
1507  
1508  
1509  
1510  
1511  
1512  
1513  
1514  
1515  
1516  
1517  
1518  
1519  
1520  
1521  
1522  
1523  
1524  
1525  
1526  
1527  
1528  
1529  
1530  
1531  
1532  
1533  
1534  
1535  
1536  
1537  
1538  
1539  
1540  
1541  
1542  
1543  
1544  
1545  
1546  
1547  
1548  
1549  
1550  
1551  
1552  
1553  
1554  
1555  
1556  
1557  
1558  
1559  
1560  
1561  
1562  
1563  
1564  
1565  
1566  
1567  
1568  
1569  
1570  
1571  
1572  
1573  
1574  
1575  
1576  
1577  
1578  
1579  
1580  
1581  
1582  
1583  
1584  
1585  
1586  
1587  
1588  
1589  
1590  
1591  
1592  
1593  
1594  
1595  
1596  
1597  
1598  
1599  
1600  
1601  
1602  
1603  
1604  
1605  
1606  
1607  
1608  
1609  
1610  
1611  
1612  
1613  
1614  
1615  
1616  
1617  
1618  
1619  
1620  
1621  
1622  
1623  
1624  
1625  
1626  
1627  
1628  
1629  
1630  
1631  
1632  
1633  
1634  
1635  
1636  
1637  
1638  
1639  
1640  
1641  
1642  
1643  
1644  
1645  
1646  
1647  
1648  
1649  
1650  
1651  
1652  
1653  
1654  
1655  
1656  
1657  
1658  
1659  
1660  
1661  
1662  
1663  
1664  
1665  
1666  
1667  
1668  
1669  
1670  
1671  
1672  
1673  
1674  
1675  
1676  
1677  
1678  
1679  
1680  
1681  
1682  
1683  
1684  
1685  
1686  
1687  
1688  
1689  
1690  
1691  
1692  
1693  
1694  
1695  
1696  
1697  
1698  
1699  
1700  
1701  
1702  
1703  
1704  
1705  
1706  
1707  
1708  
1709  
1710  
1711  
1712  
1713  
1714  
1715  
1716  
1717  
1718  
1719  
1720  
1721  
1722  
1723  
1724  
1725  
1726  
1727  
1728  
1729  
1730  
1731  
1732  
1733  
1734  
1735  
1736  
1737  
1738  
1739  
1740  
1741  
1742  
1743  
1744  
1745  
1746  
1747  
1748  
1749  
1750  
1751  
1752  
1753  
1754  
1755  
1756  
1757  
1758  
1759  
1760  
1761  
1762  
1763  
1764  
1765  
1766  
1767  
1768  
1769  
1770  
1771  
1772  
1773  
1774  
1775  
1776  
1777  
1778  
1779  
1780  
1781  
1782  
1783  
1784  
1785  
1786  
1787  
1788  
1789  
1790  
1791  
1792  
1793  
1794  
1795  
1796  
1797  
1798  
1799  
1800  
1801  
1802  
1803  
1804  
1805  
1806  
1807  
1808  
1809  
1810  
1811  
1812  
1813  
1814  
1815  
1816  
1817  
1818  
1819  
1820  
1821  
1822  
1823  
1824  
1825  
1826  
1827  
1828  
1829  
1830  
1831  
1832  
1833  
1834  
1835  
1836  
1837  
1838  
1839  
1840  
1841  
1842  
1843  
1844  
1845  
1846  
1847  
1848  
1849  
1850  
1851  
1852  
1853  
1854  
1855  
1856  
1857  
1858  
1859  
1860  
1861  
1862  
1863  
1864  
1865  
1866  
1867  
1868  
1869  
1870  
1871  
1872  
1873  
1874  
1875  
1876  
1877  
1878  
1879  
1880  
1881  
1882  
1883  
1884  
1885  
1886  
1887  
1888  
1889  
1890  
1891  
1892  
1893  
1894  
1895  
1896  
1897  
1898  
1899  
1900  
1901  
1902  
1903  
1904  
1905  
1906  
1907  
1908  
1909  
1910  
1911  
1912  
1913  
1914  
1915  
1916  
1917  
1918  
1919  
1920  
1921  
1922  
1923  
1924  
1925  
1926  
1927  
1928  
1929  
1930  
1931  
1932  
1933  
1934  
1935  
1936  
1937  
1938  
1939  
1940  
1941  
1942  
1943  
1944  
1945  
1946  
1947  
1948  
1949  
1950  
1951  
1952  
1953  
1954  
1955  
1956  
1957  
1958  
1959  
1960  
1961  
1962  
1963  
1964  
1965  
1966  
1967  
1968  
1969  
1970  
1971  
1972  
1973  
1974  
1975  
1976  
1977  
1978  
1979  
1980  
1981  
1982  
1983  
1984  
1985  
1986  
1987  
1988  
1989  
1990  
1991  
1992  
1993  
1994  
1995  
1996  
1997  
1998  
1999  
2000  
2001  
2002  
2003  
2004  
2005  
2006  
2007  
2008  
2009  
2010  
2011  
2012  
2013  
2014  
2015  
2016  
2017  
2018  
2019  
2020  
2021  
2022  
2023  
2024  
2025  
2026  
2027  
2028  
2029  
2030  
2031  
2032  
2033  
2034  
2035  
2036  
2037  
2038  
2039  
2040  
2041  
2042  
2043  
2044  
2045  
2046  
2047  
2048  
2049  
2050  
2051  
2052  
2053  
2054  
2055  
2056  
2057  
2058  
2059  
2060  
2061  
2062  
2063  
2064  
2065  
2066  
2067  
2068  
2069  
2070  
2071  
2072  
2073  
2074  
2075  
2076  
2077  
2078  
2079  
2080  
2081  
2082  
2083  
2084  
2085  
2086  
2087  
2088  
2089  
2090  
2091  
2092  
2093  
2094  
2095  
2096  
2097  
2098  
2099  
2100  
2101  
2102  
2103  
2104  
2105  
2106  
2107  
2108  
2109  
2110  
2111  
2112  
2113  
2114  
2115  
2116  
2117  
2118  
2119  
2120  
2121  
2122  
2123  
2124  
2125  
2126  
2127  
2128  
2129  
2130  
2131  
2132  
2133  
2134  
2135  
2136  
2137  
2138  
2139  
2140  
2141  
2142  
2143  
2144  
2145  
2146  
2147  
2148  
2149  
2150  
2151  
2152  
2153  
2154  
2155  
2156  
2157  
2158  
2159  
2160  
2161  
2162  
2163  
2164  
2165  
2166  
2167  
2168  
2169  
2170  
2171  
2172  
2173  
2174  
2175  
2176  
2177  
2178  
2179  
2180  
2181  
2182  
2183  
2184  
2185  
2186  
2187  
2188  
2189  
2190  
2191  
2192  
2193  
2194  
2195  
2196  
2197  
2198  
2199  
2200  
2201  
2202  
2203  
2204  
2205  
2206  
2207  
2208  
2209  
2210  
2211  
2212  
2213  
2214  
2215